

GBL-D15 通用型直流无刷电机驱动器 GBL-D15 Universal Brushless DC Motor Driver

产品特点 Product Features

- 可驱动小于 300W 无刷电机
- 可进行加减速时间设定
- 拥有功率保护功能（最大电流设定）
- 可使用外部电位器调速
- 可使用 PWM 调速
- 可使用外部模拟电压调速
- Can drive brushless motor less than 300W
- Acceleration and deceleration time can be set
- Power protection (maximum current setting)
- Speed adjustment using external potentiometer
- Can use PWM speed regulation
- Adjustable speed with external analog voltage



产品规格 Product Specification

| 项目 Item | 单位 Units | 参数 Parameters |
|------------------------------|----------|---|
| 输入电压 Input voltage | VDC | 最小值 : 12; 典型值 : 48; 最大值 : 56。 Minimum value: 12; Typical value: 48; Maximum: 56 |
| 输出电流 Output current | A | 15 |
| 霍尔信号电压 Hall signal voltage | V | 5 |
| 霍尔驱动电流 Hall drive current | mA | 172 |
| 外接电位器 External potentiometer | kΩ | 10 |
| 输入模拟量电压 Input analog voltage | VDC | 5 |
| 速度控制范围 Speed control range | RPM | 2000 |

功能选择设定 Function Selection Settings

电机极对数设定选择

为更好的匹配不同极对数的直流无刷电机，驱动器设有极对数设定选择，通过 SW1 拨码可以设定到电机极对数 4 对极或 2 对极，出厂设置为 4 对极。

PID 闭环设定选择

为了提升运行过程中的负载变动的速度稳定性，GBL-D15 驱动器设有 PID 闭环控制选择功能，通过驱动器侧面的 SW2 拨码可以进行模式选择，出厂设置为开环控制。

最大电流输出设定

最大输出电流的设定是为了保护直流无刷电机在过载运行时不被损坏，此功能是通过启动驱动器的过流报警并停止驱动器的运行来实现的。设定值应与电机的额定电流相匹配并注意实际使用的电源电压。设定范围：3~15A。

加 / 减速时间设定

电位器可设置电机加速度与减速度时间，加速时间是电机从停止到达额定转速所需的时间，减速时间是电机从额定转速到电机停止所需的时间，通过左右旋转可以调节加减速时间，设定范围：0.3~15s。

Pole logarithm setting selection of motor

In order to better match the brushless dc motor with different pole logarithm, the driver is equipped with the option of setting the pole logarithm. Through the SW1 dial code, the motor pole logarithm 4 pairs or 2 pairs can be set. The factory setting is 4 pairs.

PID closed-loop setting selection

In order to improve the speed stability of load changes during operation, the GBL-D15 driver is equipped with PID closed-loop control selection function. Mode selection can be made through the SW2 dial code on the driver side, and the factory setting is open loop control.

Maximum current output setting

The output setting of the maximum current is to protect the brushless dc motor from being damaged when it is in overload operation. This is achieved by starting the overcurrent alarm of the drive and stopping the operation of the drive. The setting value should match the rated current value of the motor and pay attention to the actual power supply voltage. Setting range: 3~15A.

Acceleration/deceleration time setting

The potentiometer can set the acceleration and deceleration time of the motor. The acceleration time is the time required for the motor to reach the rated speed from the stop, and the deceleration time is the time required for the motor to stop from the rated speed. The acceleration and deceleration time can be adjusted by rotating the potentiometer. Setting range: 0.3~15s.

Drum Motor

■ 端口信号说明 Port Signal Specification

| CN5 端子编号 CN5 Terminal Number | 信号种类 Signal types | 信号说明 Signal instructions |
|---------------------------------|--------------------------|---|
| DC+ | 电源连接 Power connection | 直流电源接入正极 (电压范围: 12-56VDC) DC power access positive pole (voltage range: 12-56VDC) |
| DC- | | 直流电源接入负极 DC power is connected to the negative electrode |
| W | 电机连接 Motor connection | 直流无刷电机 W 相 DC brushless motor W phase |
| V | | 直流无刷电机 V 相 DC brushless motor V phase |
| U | | 直流无刷电机 U 相 DC brushless motor U phase |
| REF+ | 霍尔信号 Hall signal | 直流无刷电机霍尔信号电源线 DC brushless motor hall signal power wire |
| HW | | 直流无刷电机霍尔信号 HW DC brushless motor hall signal HW |
| HV | | 直流无刷电机霍尔信号 HV DC brushless motor hall signal HV |
| HU | | 直流无刷电机霍尔信号 HU DC brushless motor hall signal HU |
| REF- | | 直流无刷电机霍尔信号接地线 DC brushless motor hall signal ground wire |
| SV | 控制信号 Control signal | 调速信号输入端口, 外部电位器调速时中间引出端连接此处, 两侧分别接 REF+ 与 COM 端口 Speed regulating signal input port. When the external potentiometer is regulation, the middle outlet end is connected here, and both sides are connected to REF+ and COM ports respectively |
| COM | | 公共端口 (0V 参考电平) Public port (0V reference level) |
| F/R | 控制信号 Control signal | 电机转动方向控制端口, F/R 端口与 COM 端口断开电机为顺时针转动, 短接闭合为逆时针转动 Motor rotation direction control port, F/R port and COM port disconnect motor for clockwise rotation, short connection closure for counterclockwise rotation |
| EN | | 停止信号控制端, EN 端口与 COM 端口断开为电机缓慢停止, 短接闭合为正常运行 Stop signal control end, EN port and COM port disconnect of slow motor stop, short connection closure of normal operation |
| BRK | | 电机快速刹车信号端口, BRK 端口与 COM 端口断开电机为快速刹车, 短接闭合为正常运行 Motor fast brake signal port, BRK port and COM port disconnection motor for fast brake, short closure for normal operation |
| SPEED | 输出信号 Output signal | 速度信号输出端口, 与电机轴转速成正比, 输出与转速成正比的频率 The output port of the speed signal is in connection to the rotation speed of the motor and the corresponding output frequency is proportional to the speed |
| ALM | | 报警信号输出端口, 正常为 5V, 出现故障时电平为 0V The alarm signal output port is 5V and the level is 0V in case of failure |

■ 外形尺寸 Overall Dimensions



